

**Birtaster und Zubehör**

**29 0790 02 - Birtaster mit Ruf- und Lichttaste, 3 m**

Der Birtaster mit Ruftaste ist ein wassergeschützter Taster mit flexibler Anschlussleitung (3 m), einer roten Ruftaste und einer gelben Lichttaste zum Schalten einer Lichtquelle. Er wird steckbar an einen Ruftaster mit Steckvorrichtung (29 0704 00...) angeschlossen.

Bei entsprechendem Anschluss der Lichtquelle ist zusätzlich zur Lichtschaltung eine Dimmfunktion möglich. Langes Drücken der Lichttaste führt dann zum Dimmen des Lichts.

**Technische Daten**

Nennspannung	24 V=
Gehäusematerial	ABS
Schutzart	IP 67
Umgebungstemperatur	+5 °C – +40 °C
Relative Luftfeuchtigkeit	0 % – 95 %

**70 0361 00 - Geräte- und Kabelhalter**

Der Geräte- und Kabelhalter dient zur Befestigung von Patientengeräten wie z.B. Birtastern am "Bettgalgen".

Bei Zugbelastung öffnet sich der Geräte- und Kabelhalter und schützt somit das Gerät vor Beschädigung. Er ist geeignet für Leitungen oder Schläuche mit einem Durchmesser von 4 - 6 und 9 mm.

Durch den symmetrischen Aufbau können zur Verdoppelung der Haltekraft zwei Geräte- und Kabelhalter spiegelverkehrt zusammengesetzt werden.

**29 0790 04 - Birtaster Abwurfvorrichtung**

Die Birtaster Abwurfvorrichtung wird zwischen den Stecker eines Birtasters (29 0790 xx) und die Buchse eines Ruftasters mit Steckvorrichtung (29 0704 00...) gesteckt.

Die Verbindung trennt bei Beanspruchung durch Zug automatisch und schützt die Geräte somit vor Beschädigung. Länge: 20 cm.

**29 0790 06 - Birtasterverlängerung, 3 m**

Die Birtasterverlängerung dient zur Verlängerung der Anschlussleitung für einen Birtaster (29 0790 xx) auf 6 m.

**Pear push switch and accessories**

**29 0790 02 - Pear push switch incl. call & light switch, 3m**

The pear push switch incl. call and light switch is a water-protected push-button with a flexible connecting cable (3 m), a red call button and a yellow light push-button for switching a light source. It is connected to a call switch with connector (29 0704 00...).

When connected to an appropriate light source an additional dimming function is also possible. A long press of the light push-button then causes the light to dim.

**Technical data**

Nominal voltage	24 V=
Housing material	ABS
Degree of protection	IP 67
Ambient temperature	+5°C – +40°C
Relative humidity	0 % – 95 %

**70 0361 00 - Equipment and cable clamp**

The equipment and cable clamp serves for fixing patient devices such as pear push switches on the "Bed-gallows".

When put under tensile load the equipment and cable clamp opens and so protects the device against damage. It is suitable for conduits or hoses with a diameter of 4 - 6 and 9 mm.

The symmetric structure allows two equipment and cable clamps to be mounted mirror-inverted to double the holding force.

**29 0790 04 - Self-releasing adapter for pear push switch**

The self-releasing adapter for the pear push switch is plugged between the plug of a pear push switch (29 0790 xx) and the socket of a call switch with connector (29 0704 00...).

When under load, the connection separates automatically under tension and so protects the device against damage. Length: 20 cm.

**29 0790 06 - Extension cable for pear push switch, 3 m**

The extension cable for the pear push switch serves as extension for the connecting cable of pear push switch (29 0790 xx) to 6 m.

© Tunstall GmbH, Orkotten 66, 48291 Telgte, Germany, www.tunstall.de

